

## Wiring Configuration for Pushbutton and Key Switch

Actual mounting of RLD with Pushbutton and Key Switch is subject to the local Authority Having Jurisdiction (AHJ). The following describes the wiring configuration of the Pushbutton and Key Switch to the RLD.

1. (Refer to diagram below) The Key Switch (part # 3124) has four black wires protruding from the underside. The wires are pre-stripped and ready for installation. The wires are marked, respectively, 8, 1, 2, and 3. These will be attached to the terminals of TB6 on the underside of the RLD, according to the outline below.

Wire 8 to Terminal 5  
Wire 1 to Terminal 6  
Wire 2 to Terminal 9  
Wire 3 to Terminal 8

2. The Pushbutton (part # 3150) has two (2) wires protruding from the underside. One is black and one is red. Attach these wires to TB6, according to the outline below.

Black Wire to Terminal 7  
Red Wire to Terminal 9



